Liquid Series Thermoelectric Cooler Assembly

The DL-210-24-00 thermoelectric cooler assembly offers dependable, compact performance by cooling objects via liquid to transfer heat. Heat is absorbed through a cold block and dissipated thru a second liquid heat exchanger. The thermoelectric modules are custom designed to achieve a high coefficient of performance (COP) to minimize power consumption. It has a maximum Qc of 265 Watts when ΔT = 0 and a maximum ΔT of 42 °C at Qc = 0. The liquid heat exchanger is designed to accommodate distilled water with glycol. Corrosion resistant turbulators are enclosed inside channels to increase heat transfer. Mating port adaptors are sold separately.

Features

- Compact design
- Precise temperature control
- Reliable solid-state operation
- DC operation
- RoHS-compliant

Applications

- Medical Diagnostics
- Industrial Lasers
- Medical Lasers
- Analytical Instrumentation



Electrical and Thermal Performance





Coefficient of Performance (COP = Qc/Pin)
Tambient = 35°C



Coefficient of Performance (COP = Qc/Pin)
Tambient = 35°C



Total Heat Dissipated at Hot Side (Qh=Qc+Pin)
Tambient = 35°C



Total Heat Dissipated at Hot Side (Qh=Qc+Pin)
Tambient = 35°C



Heat Pumped at Cold Side (Qc)
Voperating = 24 Volts | Ioperating = 8.73 Amps



Coefficient of Performance (COP = Qc/Pin)
Voperating = 24 Volts | Ioperating = 8.73 Amps





Specifications

Heat Transfer Mechanism, Cold Side	Direct - Conduction
Heat Transfer Mechanism, Hot Side	Liquid - Forced Convection
Operating Temperature Range	-40°C to 62°C
Supply Voltage	24.0 VDC nominal / 28.0 VDC maximum
Current Draw	7.8 A running / 8.5 A startup
Power Supply	221.0 Watts
Performance Tolerance	10%
Hi-Pot Testing	750 VDC
Over-Temp Thermostat (Hot and Cold Side Heat Sink)	75°C ±5°C (hot side heat sink)
Weight	1.30 kg
Panel Mounting	Flush Mount

Mounting Hole Location



INCHES [MM]

Electrical Connections

TEM+ : Red
TEM - : Black

Wire Size: 18 AWG

The overheat protection (OHT) bimetal thermostat has a maximum current of 8 Amps. For systems 8 Amps or less, the thermostat can be connected directly in series with thermoelectric modules (TEMs). Otherwise connect the TEMs to the power source through a relay of suitable rating which state is controlled with the bimetal thermostat.

Notes

[1]Cold block requires insulation to minimize moisture buildup under dew point conditions.

Revision: 00 Date: 06-01-2022

Print Date: 05-12-2025